

## **502 and 504 REMOTE CONTROLS MANUAL PROGRAMMING**

The manual programming allows you to assign a code to every channel as required. (12 bit binary logic on or off) There are no dip-switches inside the case; it is a virtual dip-switch set up. This procedure can be used also for the modification of the inserted (factory setting) codes.

Press and hold the top two buttons at the same time, when the LED begins to flash let go. (Fig1)



Press once the relative key to which you want to programme, the LED goes solid. (Fig 2)

Now press once the top left key this puts the dip 1 to ON, pressing once the top right will now put the dip 2 OFF and so on..... Until you reach the twelfth dip, then the transmitter exits from the programming procedure.

Do not use all ON OFF ON OFF.....ON OFF or all OFF or all ON, this is two obvious.

When you have successfully completed the coding, you will need to learn this code to your radio receiver using the manufacturers instructions.

If you do nothing for 12 seconds the transmitter exits set up and nothing is stored.



Battery replacement. Remove the screw here

